

DCP-400

The **DCP-400** detector can detect the early stages of fire development when there is a temperature rise. It is designed to be used in conjunction with the **ACSP-402** fire alarm control panel.

- heat sensor
- LED indicator
- double-sided short-circuit isolator
- power supply from the detection line
- installation on the **DB-400** base by SATEL (sold separately)
- ability to connect the **WZ-110** remote indicator
- dust cover included



| | |
|--|--------------|
| Enclosure dimensions | ø108 x 54 mm |
| Operating temperature range | -25...+50 °C |
| Weight | 94 g |
| Maximum humidity | 93±3% |
| Class according to EN 54-5 (heat sensor) | A1R |
| Minimum static response temperature | 54 °C |
| Maximum static response temperature | 65 °C |
| Current draw when detecting | 450 µA |
| Current draw when emitting an alarm | 0,6 mA |
| Power supply voltage | 18...26 V DC |