

DRP-400

The **DRP-400** detector can detect the early stages of fire development when there is some visible smoke. It is designed to be used in conjunction with the **ACSP-402** fire alarm control panel.

- visible smoke sensor
- detection of dirt buildup in the optical chamber
- smoke sensor sensitivity adjusted by the control panel (4 sensitivity levels)
- LED indicator
- double-sided short-circuit isolator
- power supply from the detection line
- installation on the **DB-400** base by SATEL (sold separately)
- ability to connect the **WZ-110** remote indicator
- dust cover included



Enclosure dimensions	ø108 x 46 mm
Operating temperature range	-25...+50 °C
Weight	94 g
Maximum humidity	93±3%
Minimum static response temperature	54 °C
Maximum static response temperature	65 °C
Current draw when detecting	450 µA
Current draw when emitting an alarm	700 µA
Power supply voltage	18...26 V DC